

Digital Multimeter

DM-91



Features:

- 3½ Digital Multimeter
- Inter locking Terminal
- Built in Hanging Kit



Technical Data :

Basic Functions	Range	Basic Accuracy
DC Voltage	200mV 2V, 20V, 200V 1000V	±(0.5% + 1d) ±(0.5% + 3d) ±(0.8% + 3d)
AC Voltage	2V, 20V, 200V 700V	±(1.0% + 5d) ±(1.2% + 5d)
DC Current	20uA 2mA 200mA 10A	±(1.2% + 3d) ±(1.0% + 3d) ±(1.5% + 5d) ±(2.0% + 10d)
AC Current	20mA 200mA 10A	±(1.2% + 5d) ±(2.0% + 5d) ±(3.0% + 10d)
Resistance	200Ω 2KΩ, 20KΩ, 200KΩ 20MΩ 200MΩ	±(1.0% + 10d) ±(1.0% + 1d) ±(1.0% + 5d) ±[5.0% (rdg-10d) + 20d]
Capacitance	2nF, 200nF, 2uF 200uF	±(4.0% + 3d) ±(5.0% + 3d)
Frequency Testing	200KHz	±(1.5% + 10 digits)
Temperature	-20°C to 1000°C	±(1.0% + 3)

Special Function :

Diode test	✓
Transistor Testing	✓
Continuity Buzzer	Approx. < 70Ω
Power	9V (6F22)

- **Standard Accessories** : Test Leads, Holster, Manual
- **Dimension** : 185(H) x 93(W) x 35(D)mm