

CM-2030

AC Clamp Meter(1000 Ampere)

HTCTM
INSTRUMENTS

Features:

- 3 1/2 MANUAL AC CLAMP METER.
- FULLY PROTECTED in the RANGE
- CLAMP OPEN: 52mm.
- Clamp Torch.



Technical data:

Function	Range	Resolution	Accuracy
DC VOLTAGE (DCV)	1000V	1V	$\pm(0.8\%+2)$
AC VOLTAGE (ACV)	750V	1V	$\pm(1.0\%+5)$
AC Current (ACA)	200A	0.1A	$\pm(3.0\%+5)$
	1000A	1A	
Resistance (Ω)	200 Ω	0.1 Ω	$\pm(1.0\%+3)$
	20k Ω	10 Ω	
	200k Ω	100 Ω	
Diode and Continuity	Description	Test Condition	
	Diode forward voltage drop.	Forward DC Current is approx 1mA, Reserve DC voltage is less than 3V.	
	When resistance is less then 30 \pm 10 Ω , buzzer sounds	Open circuit voltage is about 3V	

- **Standard Accessories** : Soft Carrying case, Manual, Probe
- **Dimension** : 123(H) x270(W) x 35(D)mm

