

KUSAM-MECO

An ISO 9001:2008 Company

DIGITAL SOUND LEVEL METER

Model KM 929 MK1

Sound Level Meter has been designed to meet the measurement requirement of noise engineers, noise quality control & health prevention in various environments, such as noise measurement in factory, Office, Traffic Road, Family & all other noise measurement applications.

FEATURES :

- A/C Frequency weighting selection
- Automatic Backlight
- Auto Power off 10 minutes
- PWM signal output
- Calendar function
- 4700 data record function

GENERAL SPECIFICATIONS :

- Measuring Range : 30 ~ 130 dBA, 35 ~ 130 dBC
- Accuracy : ± 1.5 dB
- Resolution : 0.1 dB
- Display : 5 Digits display
- Frequency Response : 31.5Hz ~ 8.5KHz
- Measuring Level : 30 ~ 130, 40 ~ 90, 50 ~ 100, 60 ~ 110, 80 ~ 130
- Frequency weighting : A & C
- Time Weighting : FAST / SLOW
- Sampling rate : 2 times / second
- Microphone : 1/2 inch polarization capacitance microphone
- USB interface
- AC / PWM output
- Max reading
- Overload indication : OVER / UNDER
- Low battery indication
- Power Supply : 4 x 1.5V AA or DC 6V 100mA adapter
- Dimension : 70 x 35 x 256 mm
- Weight : Approx. 308g (including battery)

SAFETY :

- IEC PUB 651 TYPE2 ,
ANSI S1.4 TYPE2



Preliminary Data

All Specifications are subject to change without prior notice.

KUSAM-MECO

An ISO 9001:2008 Company

G-17, Bharat Industrial Estate, T. J. Road, Sewree (W), Mumbai - 400 015. INDIA.
Sales Direct.: 022-24156638, **Tel. :** 022-24124540, 24181649, **Fax :** 022-24149659
Email : kusam_meco@vsnl.net, **Website :** www.kusamelectrical.com