

# Lux Meter

## LX-101A/LX-102A



### Features:

- DATA HOLD
- Auto Power OFF
- PEAK HOLD(LX-102A)



### Technical Data :

Basic Function		LX-101A	LX-102A
Range	LUX	0~2,00,000 LUX	0~2,00,000 LUX
	FC	--	0~20,000 FC
ACCURACY		±5% of reading	
Receiving light		Silicon of photo electricity diode	
Low Battery display		•	
Power Source		1x9.0V (6F22)	

- **Standard Accessories** : Soft carrying case, Manual
- **Dimension** : Photo Detector : 82(H) x 55(W) x 7(D)mm  
Meter Body : 148(H) x 70(W) x 40(D)mm

