



INTRODUCTION

RTD-CAL-408 Calibrator is useful for calibration & testing of all instruments having RTD input, like Digital Temp. Indicator, Controller, PID, Scanner, Transmitters etc.

RTD OUTPUT

FIX RANGE OUTPUT

To get fix range O/P -200 to +600 °C

'FIX RANGE OUTPUT', Corresponding output you will get from RTD O/P Terminal in OHMS.

O/P SELECTION : RTD O/P & RTD LWC O/P

| | |
|----------------------|---|
| FIX RANGE O/P | -200, -100, -50, -25, 0, +25, 50, 100, 150, 200, 250, 300, 350, 400, 500, 600°C |
| ACCURACY | ± 0.05% |
| BOX SIZE | 133 mm X 188 mm |

*Technical Specifications & Appearance are subject to change without prior notice